



**CD3**  
**Video Security**

www.eyespyvideo.com  
 24 Hour Sales: 800-568-6871  
 Customer Service: 800-568-9291 (9am - 5pm Central US)  
 Fax: 800-568-6356  
 info@eyespyvideo.com

## PWR-IN3 Information



The **PWR-IN3** is a 12v DC to 110v AC power inverter. Voltage output is provided from two (2) grounded 3-prong just like any standard U.S. 110v AC wall outlet. The PWR-IN3 can deliver up to 300 watts of AC electrical current.

Voltage input is 13.8v DC (from an automotive or marine battery). Connection to the battery can be made in two ways: connect to an automobile cigarette lighter DC output jack with the included automotive adapter plug or directly to the battery's positive and negative terminals using the the included alligator clips. The PWR-IN3 can deliver up to 300 watts continuous AC power when connected to the battery's terminals and up to 150 watts continuous AC power when plugged into a cigarette lighter outlet.

This device is a great and economical way to power 110v VCR recorders, TV monitors, and other equipment in a mobile capacity.

## PWR-IN3 Technical Specification

Input Voltage	13.8 volts DC for most automotive batteries
Output Voltage	U.S. 110v AC, 60 Hz
Current Delivery	up to 300 W (watts) max. continuous power with alligator clips, up to 150 W (watts) max. continuous power with cigarette plug
Input Plug	fused polarized alligator clips for battery connection, fused automotive cigarette lighter power outlet plug
Output Plug	2 x U.S. grounded 110v 3-prong wall outlet
Cord Length	36" / 914mm for polarized alligator clips, 34" / 864 for automotive cigarette lighter power outlet plug
Battery Low Alarm	@ 10.5v DC +/- 0.5v
Battery Low Shutdown	@ 10.0v DC +/- 0.5v
Dimensions	9.1" x 4.1" x 2.3" / 232mm x 104mm x 58mm
Weight	1 lb., 10oz. / 739g
Warranty	one year
*Additional Features	enables the mobile use of 110v AC DVR & VCR video recorders, video quads and multiplexers, and many other devices