



CD3
Video Security

www.eyespyvideo.com
 24 Hour Sales: 800-568-6871
 Customer Service: 800-568-9291 (9am - 5pm Central US)
 Fax: 800-568-6356
 info@eyespyvideo.com

PWR-IN6 Information



The **PWR-IN6** is a 12v DC to 110v AC power inverter. Voltage output is provided from two (2) grounded 3-prong just like any standard U.S. 110v AC wall outlet. The PWR-IN6 can deliver up to 600 watts of AC electrical current.

Voltage input is 13.8v DC (from an automotive or marine battery). Connection is made directly to the battery's positive and negative terminals using the the included alligator clips.

This device is a great and economical way to power 110v VCR recorders, TV monitors, and other equipment in a mobile capacity.

PWR-IN6 Technical Specifications

Input Voltage	13.8 volts DC for most automotive batteries
Output Voltage	U.S. 110v AC, 60 Hz
Current Delivery	up to 600 W (watts) max. continuous power
Input Plug	polarized alligator clips for battery connection
Output Plug	2 x U.S. grounded 110v 3-prong wall outlet
Cord Length	5' / 1.5 meters
Battery Low Alarm	@ 10.5v DC +/- 0.5v
Batter Low Shutdown	@ 10.0v DC +/- 0.5v
Dimensions	12" x 8.4" x 2.5" / 305mm x 213mm x 64mm
Weight	5 lbs. / 2.3 kg
Warranty	one year
*Additional Features	enables the mobile use of 110v AC DVR & VCR video recorders, video quads and multiplexers, and many other devices